AD 2 BATTERY *INT

For the fast, dust-free cleaning of fireplaces, pellet heating systems or charcoal barbecues: our battery powered ash vacuum AD 2 Battery.



Made in Europe

18V

BATTERY NOT INCLUDED

REAL TIME TECHNOLOGY

KÄRCHER ReBoost FILTER CLEANING

3 × PUSH

Order no. **1.348-300.0**

- Filter cleaning, leaning position
- 18 V battery platform, 14 l metal container, 1.2 m hose
- Flame-resistant flat pleated filter

Technical data		
EAN code		4054278662060
Battery powered device		1
Battery platform		18 V battery platform
Rated input power	**W**	200
Suction Power	**W**	45
Vacuum	**mbar**	max. 95
Air flow	**l/s**	max. 22
Container capacity	**l**	14
Nominal size of accessory	**mm**	35
Battery type		Lithium-ion exchangeable battery
Voltage	**V**	18
Run time per battery charge	**min**	approx. 13 (2.5 Ah) / approx. 25 (5.0 Ah)
Sound power level	**dB(A)**	78
Colour		Black
Weight without accessories	**kg**	3.9
Weight incl. packaging	**kg**	6
Dimensions (L × W × H)	**mm**	328 × 343 × 431

Scope of supply

Versions: Battery and battery charger not included
Suction hose length: 1.2 m
Suction hose material: metal, coated
Coarse dirt filter
Coarse dirt filter, material: Metal

Equipment

Flat pleated filter: Polyester, flame-resistant
Container material: Metal
Filter cleaning function
Leaning position for suction hoseLeaning position for suction hose
Comfortable handle on containerComfortable handle on container
Storage space for small parts

[2] By using the Kärcher filter cleaning system, the suction power is restored up to 80% after five vacuuming and filter-cleaning cycles. Based on internal tests at orifice 10 mm.

AD 2 Battery *INT, 1.348-300.0, 2026-11-06





18 V Kärcher Battery Power exchangeable battery

- Maximum freedom of movement thanks to cordless flexibility.
- Real Time Technology with LCD display for displaying the battery charging state.
- Compatible with all devices in the 18 V Kärcher Battery Power platform.



1-part filter system (flame-resistant) with flat pleated filter and metal coarse dirt filter

- To easily drain and clean the container without coming into contact with dirt.
- Extremely high level of comfort thanks to the fast filter removal in just one step.



Flame-resistant material, metal container and metal hose (jacketed)

- Maximum safety when vacuuming ash – also with improper use.

AD 2 Battery *INT, 1.348-300.0, 2026-11-06

KÄRCHER

ACCESSORIES FOR AD 2 BATTERY *INT
1.348-300.0


1


2


3, 5


4, 6


7


8


9


10


11

		Order no.	Description	
VACUUMS				
Filters				
Flat pleated filter KFI 7420	1	6.415-953.0	Flat pleated filter KFI 7420 for long-lasting suction power[2].	■
Nozzles				
Extra-long crevice nozzle	2	2.863-307.0	Extra-long crevice nozzle (350 mm) made from flame-resistant material for vacuuming cold ash. Suitable for all Kärcher ash vacuum cleaners from the Home & Garden range.	☐
BATTERIES				
Battery Power 18/25	3	2.445-034.0	18 V / 2.5 Ah Kärcher Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to indicate battery level. Suitable for use in all devices on the 18 V Kärcher battery platform.	☐
Battery Power 18/50	4	2.445-035.0	18 V / 5.0 Ah Kärcher Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to indicate battery level. Suitable for use in all devices on the 18 V Kärcher battery platform.	☐
Battery Power 18/25	5	2.445-100.0	18 V / 2.5 Ah Kärcher Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to indicate battery level. Suitable for use in all devices on the 18 V Kärcher battery platform.	☐
Battery Power 18/50	6	2.445-103.0	18 V / 5.0 Ah Kärcher Battery Power exchangeable battery with innovative Real Time Technology incl. LCD display to indicate battery level. Suitable for use in all devices on the 18 V Kärcher battery platform.	☐
Battery Power 18/80	7	2.445-106.0		☐
BATTERY CHARGERS				
Fast Charger Battery Power 18 V	8	2.445-032.0	The fast charger charges the 18 V/2.5 Ah Kärcher Battery Power exchangeable battery to 80% in just 44 minutes and can be used for all batteries on the 18 V Kärcher battery platform.	☐
STARTERKIT BATTERIES AND BATTERY CHARGERS				
Starter kit Battery Power 18/25	9	2.445-062.0	Battery Power 18/25 Starter Kit incl. 18 V/2.5 Ah Battery Power exchangeable battery with innovative Real Time Technology and 18 V fast charger. For all devices on the 18 V Kärcher battery platform.	☐
Starter kit Battery Power 18/50	10	2.445-063.0	Incl. 18 V / 5.0 Ah Kärcher Battery Power exchangeable battery and 18 V fast charger: The Battery Power 18/50 Starter Kit for use in all devices on the Kärcher 18 V battery platform.	☐
BATTERIES				
Battery Power+ 18/30	11	2.445-042.0	With Real Time Technology displayed on an LCD screen: very powerful Battery Power+ 18-volt lithium-ion battery. Long runtime thanks to a capacity of 3.0 Ah. With voltage monitoring and IPX5 protection.	☐

■ Included in the scope of supply. ☐ Available accessories.